



Addressable Sounder Controller Unit

Product Overview

- Syncro addressable sounder controller units enable additional, distributed power and control for sounder circuits in situations where there are insufficient circuits at the fire alarm control panel or where additional power is required to power heavily loaded sounder circuits.
- Sounder control modules for any of the protocols supported by Syncro are available in a steel enclosure designed to match the appearance of the Syncro fire alarm control panel.
- All units contain mains powered battery charger/power supply, they have space for up to 7 Ah batteries.
- Indicators are provided for power healthy and power fault conditions and power fault conditions are signalled to the Syncro fire alarm control panel as a sounder fault.

Features

- Two, four or six way units available
- Apollo, Argus Vega or Hochiki protocols available
- Integral power supply
- Robust steel enclosure matches Syncro control panel styling
- Space for 7Ah batteries
- Power Healthy and Power Fault indicators

Technical

| | |
|-------------------------------|---|
| Size | - 500mm (W) x 355mm (H) x 108mm (D) |
| Finish | - Epoxy powder coated |
| Colour - lid & box | - BS 00 A 05 grey - fine texture |
| Colour - labels | - RAL 7047 light grey - satin |
| Mains voltage supply | - 110 or 230V AC 50 or 60 Hz. (specify when ordering, default is 230V) |
| Mains fuse | - 3A, 1¼ inch |
| Battery charge fuse | - 20mm x 5mm, 500 milliamp |
| Battery | - 7Ah 12V (2 per panel) |
| Operating temperature | - -5°C to +50°C |
| Operating humidity | - To 95% (non condensing) |
| Protocol | - Apollo XP95, Argus Vega or Hochiki ESP |

Panels

| Product Code | Protocol | Sounder Outputs | PSU |
|-----------------|-------------|-----------------|------|
| A1725203 | Apollo XP95 | 2 | 2.5A |
| V1725203 | Argus Vega | 2 | 2.5A |
| H1725203 | Hochiki ESP | 2 | 2.5A |
| A1725403 | Apollo XP95 | 4 | 4.0A |
| V1725403 | Argus Vega | 4 | 4.0A |
| H1725403 | Hochiki ESP | 4 | 4.0A |
| A1725603 | Apollo XP95 | 6 | 4.0A |
| V1725603 | Argus Vega | 6 | 4.0A |
| H1725603 | Hochiki ESP | 6 | 4.0A |



Model No. #1725203